

Power Up Your Home Safely and Affordably with GenerLink

PRODUCT DESCRIPTION

The GenerLink™ transfer switch is a UL-listed, socket-mounted device designed to provide a safe, easy, and affordable way to connect a portable generator to your home. Installed directly behind your electric meter, GenerLink™ seamlessly delivers generator power to your breaker box, eliminating the need for hazardous power cords running through your home.

Key Features of GenerLink™:

- **Automatic Grid Disconnection:** GenerLink™ detects when a generator is operating and automatically disconnects from the utility grid, eliminating the risk of dangerous backfeed.
- **Eliminates Extension Cords:** Allows homeowners to power hardwired items such as sump pumps, well pumps, lighting, and security systems without the need for extension cords.
- **GenerLok™ System:** Equipped with a unique interlocking power cord system, GenerLok™ provides a quick and easy connection to a portable generator.
- **Quick Installation:** Can be installed in 30 minutes or less by utility personnel without requiring the homeowner's presence.
- **No Rewiring Needed:** Easily installed behind the customer's electric meter, GenerLink™ requires no rewiring of the home's electrical system.
- **Flexible Appliance Usage:** Provides the flexibility to run virtually any appliance up to the generator's capacity by simply energizing appliances from the breaker panel.

With GenerLink™, enjoy the peace of mind that comes with a safer, more convenient backup power solution for your home.



5-Year Warranty



Made in Georgia



LISTED

Specifications and Technical Information Model (MA23/24 – N/S)

Physical:	Diameter:	6 1/2 in.
	Depth:	5 1/4 in.
	Weight w/o surge:	5 1/2 lbs
	Weight with surge:	5 3/4 lbs
	Socket Style:	Ring or Ring-less, 200 Amp, 4 jaw

Electrical:	Source Compatibility	200 Ampere Service or less
	Withstand Current:	14,000 Amperes rms symmetrical at .5 pf, 240 Volts, 60 Hz 6000 Amperes for 6 cycles at .7 - .8 pf, 240Volts, 60 Hz 10kW
	Generator Input:	Continuous [†] , 120/240 Volt (MA-24)
	Connection:	Proprietary GenerLok™ QuickConnect Power Cord [‡]

Operational:	Transfer Type:	Break-Before-Make
	Transfer Delay:	2-3 Seconds
	Life Cycle:	300,000 Operations
	Temperature Range:	-30°C to 60°C External Ambient

Features:	Generator Input Protection:	Generator Input Voltage ≥ 200 Volts Supplemental Overcurrent ≤ 40 A
	Utility Input Protection:	Utility Input Voltage ≥ 180 Volts Over-Temperature Trip ≥ 105°C
	Load Protection:	Integrated Whole-House, Surge Protection Model MA23/24 - S Only Type 1 - 75kA per phase
	Status Indication:	Long-life LED indicators show utility power availability and/or fault presence
	Listings:	UL 1008M - Meter socket transfer switch

[†] 3 hours at 25° C ambient

[‡] Sold Separately

* when protected by max 200 A circuit breaker in series with max 100 A branch circuit breaker

Flexible Appliance Usage:



**Refrigerators/
Freezers**



Lighting



**Well
Pumps**



**Sump
Pumps**